

## Tonos CTCSS (PL)

Frecuencia Hz	Estándar	Motorola	Alinco
67.0	1	XZ/L1	A00
69.3		WZ	C00
71.9	2	XA/L2	B00
74.4	3	WA	C01
77.0	4	XB/L3	A01
79.7	5	WB/SP	C02
82.5	6	YZ/L4	B01
85.4	7	YA	C03
88.5	8	YB/L4A	A02
91.5	9	ZZ	C04
94.8	10	ZA/L5	B02
97.4	11	ZB	C05
100.0	12	1Z	A03
103.5	13	1A	B03
107.2	14	1B	A04
110.9	15	2Z	B04
114.8	16	2A	A05
118.8	17	2B	B05
123.0	18	3Z	A06
127.3	19	3A	B06
131.8	20	3B	A07
136.5	21	4Z	B07
141.3	22	4A	A08
146.2	23	4B	B08
151.4	24	5Z	A09
156.7	25	5A	B09
159.8			
162.2	26	5B	A10
165.5			
167.9	27	6Z	B10
171.3			
173.8	28	6A	A11
177.3			
179.9	29	6B	B11
183.5			
186.2	30	7Z	A12
189.9			
192.8	31	7A	B12
196.6			
199.5			
203.5	32	M1	A13
206.5		8Z	
210.7	33	M2	B13
218.1	34	M3	A14

225.7	35	M4	B14
229.1		9Z	
233.6	36	M5	A15
241.8	37	M6	B15
250.3	38	M7	A16
254.1		OZ	

### Tonos CDCSS (DCS) (DPL)

017	145	306	465
023	152	311	466
025	155	315	503
031	156	325	506
032	162	331	516
036	165	332	523
043	172	343	526
047	174	346	532
050	205	351	546
051	212	356	565
053	223	364	606
054	225	365	612
065	226	371	624
071	243	411	627
072	244	412	631
073	245	413	632
074	246	423	654
114	251	431	662
115	252	432	664
116	255	445	703
122	261	446	712
125	263	452	723
131	265	454	731
132	266	455	732
134	271	462	734
143	274	464	743
<b>Todos los tonos pueden ser normales o invertidos.</b>			754

### Tonos DTMF

1	2	3	A	<b>697 Hz</b>
4	5	6	B	<b>770 Hz</b>
7	8	9	C	<b>852 Hz</b>
*	0	#	D	<b>941 Hz</b>
<b>1209 Hz</b>	<b>1336 Hz</b>	<b>1477 Hz</b>	<b>1633 Hz</b>	